

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Россия (495)268-04-70

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://huebsch.nt-rt.ru/> || hcs@nt-rt.ru

Huebsch®

Multi-Housing

Micro-DISPLAY Control

Washers and Stack Washer/Dryers

Horizon® Frontloaders

World Drop

HWFR71 Front Control Washer

Card Ready

HWFY71/HWY73 Front Control Washer

HTEY77/HTGY79 Stack Washer/Dryer

Dual Drop

HWFT71/HWFT73 Front Control Washer

HTET77/HTGT79 Stack Washer/Dryer

Without Coin Drop

HWFX71 Front Control Washer

HFGX07/HFGX09 Front Control Dryer

HTEX77/HTGX79 Stack Washer/Dryer



Specifications



MDC Washer MDC Washer/Dryer MDC Dryer

Micro-DISPLAY Control Coin or Card-Operated

Residents will find the laundry process a breeze with the streamlined, easy-to-use Micro-DISPLAY Control.

- Displays coin countdown to start cycle.
- Shows cycle time remaining.
- Remaining card balance on card operated units.
- Touch pad selectors for easy activation with LED and sound enunciator signal.
- Bright, easy-to-read cycle status lights.



Your authorized Huebsch route operator can design an MDC laundry room solution for any property type.

- Non-resettable cycle and coin counters to monitor laundry room activity.
- Diagnostics to expedite service.

Ultra, High-Efficiency Wash System

- The MDC offers four energy-efficient wash cycles that integrate into a six-speed wash system.
- ENERGY STAR® qualified.
- U.S. Department of Energy compliant to 2007 commercial washer standards for energy and water savings.



	Washers	Dryers	Stack W/D
	HWFR71, HWFY71, HWFY73 HWFT71, HWFT73	Electric: HFEX07 Gas: HFGX09	Electric: HTEY77, HTET77, HTEX77 Gas: HTGY79, HTGT79, HTGX79
Basket/Cylinder Volume - liters (cu. ft.)	80 (2.84)	19 (87.0)	80 (2.84) 198 (7.0)
Width - mm (in)	683 (26 7/8")	683 (26 7/8")	683 (26 7/8")
Depth - mm (in)	711 (28")	711 (28")	711 (28")
Height* - mm (in)	1092 (43")	1092 (43")	1946 (76 5/8")
Weight - kg (lb)	113 (250)	Electric: 68 (150) Gas: 70 (155)	Electric: 163 (360) Gas: 166 (365)
Shipping Weight - kg (lb)	123 (270)	Electric: 73 (160) Gas: 75 (165)	Electric: 177 (390) Gas: 179 (395)
Cycle Time - minutes	23-29	45	23-29/45
Motor HP	3/4 HP, 750 W	1/3 HP, 5.5 amps	1/3 HP, 5.5 amps 3/4 HP, 750 W
Water Consumption liters per cycle (gal.)	56.0 (14.8)	N/A	56.0 (14.8)
Water Factor liters per liter (gal.)	0.7 (5.2)	N/A	0.7 (5.2)
Modified Energy Factor	61.17 (2.16)	N/A	61.17 (2.16)
Hot Water Usage liters per cycle (gal.)	6.0 (1.59)	N/A	6.0 (1.59)
Water Pressure bar (psi)	1.4/8.3 (Pressure fill - 20 to 120)	N/A	1.4/8.3 (Pressure fill - 20 to 120)
Spin Speed - RPM	500, 650, 1000	N/A	500, 650, 1000
Cycle/Temperature	Normal/Hot Normal/Warm Perm Press/Warm Delicate/Cold	High 160° Medium 155° Low 145° Delicate 115°	High 160° Medium 155° Low 145° Delicate 115°
Electrical Specifications and Circuit Requirements Canada (U.S.)	120/60/1-15 amp (15 amp)	Electric 120/240/60/1-30 amp (30 amp) 120/208/60/1-30 amp (30 amp) Gas: 120/60/1-15 amp (15 amp)	Electric 120/240/60/1-40 amp (30 amp**) 120/208/60/1-40 amp (30 amp**) Gas: 120/60/1-20 amp (20 amp**)
Motor - RPM	Inverter Drive	60 Hz: 1725	60 Hz: 1725
Btu per Hour	N/A	25,000 (6300 kcal)	25,000 (6300 kcal)
Heating Element Canada (U.S.)	N/A	5000 W, 240 V (5350 W, 240 V) 4250 W, 208 V (4750 W, 240 V)	5000 W, 240 V (5350 W, 240 V) 4250 W, 208 V (4750 W, 240 V)
Type of Gas (Gas models only)	N/A	Factory equipped natural/ mixed gas. Convertible to LP gas.***	Factory equipped natural/ mixed gas. Convertible to LP gas.***
Utility Connections in (mm)	N/A	Gas: 3/8" NPT (9.5)	Gas: 3/8" NPT (9.5)
Air Outlet Diameter - in (mm)	N/A	4" (102)	4" (102)
Exhaust Airflow † cfm (liters/sec.)	N/A	220 (105)	220 (105)
Maximum Exhaust Static Back Pressure	N/A	0.6" W.C.	0.6" W.C.
Agency Approval	CSA	Electric: CSA Gas: CSA Flame	Electric: CSA Gas: CSA Flame
Top Finish	Porcelain	Porcelain	N/A
Colors	White	White	White
Door Type	Window	Window	Window

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижегород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Казахстан (772)734-952-31

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Россия (495)268-04-70

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93